### SAG-6838634501-12-S1

#### E-Band Gaussian Optics Antenna, 68 to 86 GHz, 12"

**SAG-6838634501-12-S1** is a 12" E-Band Gaussian antenna that operates from 68 to 86 GHz. The Gaussian antenna delivers a 45 dBi nominal gain and 1.0 degree half power beamwidth. The antenna supports linear polarized waveforms and employs a corrugated feed horn to offer excellent aperture efficiency, high cross polarization rejections and low sidelobes levels. This model is equipped with a standard WR-12 waveguide and UG-387/U flange as its input port. By removing the mode transition, Eravant model number SWT-12125-SB, the input port becomes 0.125" diameter circular waveguide, which can support both linear and circular polarized waveform.



#### **Electrical Specifications:**

Parameter	Minimum	Typical	Maximum
Frequency	68 GHz	77 GHz	86 GHz
Gain	RATION	45 dBi	
3 dB Beamwidth		1.0°	
Sidelobes		-25 dB	
Polarization		Linear	
Return Loss		15 dB	
Specification Temperature		+25 °C	
Operating Temperature	-40 °C		+85 °C

#### **Mechanical Specifications:**

Item	Specification
Antenna Port	WR-12 Waveguide with UG-387/U Flange
Housing Material	Aluminum
Housing Finish	Black Anodized
Weight	19.5 lbs
Lens Diameter	12"
Dimensions	13.00" (Ø) x 17.22" (L)
Outline	AG-RE45

#### www.eravant.com | 424-757-0168 | support@eravant.com Copyright © 2022 by Eravant

#### ECCN

EAR99

#### FEATURES

- Center Fed
- Low Sidelobes
- Low Cross Polarization

#### **APPLICATIONS**

- Radar Systems
- Communication Systems
- Plasma Systems

#### SUPPLEMENTAL DETAILS



### SAG-6838634501-12-S1

#### **Mechanical Outline:**

Unless otherwise specified, all dimensions are in inches [millimeters])



#### NOTE:

- On condition that test data is provided it is collected from a sample lot. Actual data may vary slightly from unit to unit. All testing is performed under +25 °C room temperature.
- On condition that simulated test data is provided, actual measured data may slightly vary.
- Eravant reserves the right to change the information presented without notice.

#### CAUTION:

- If a waveguide is present, any foreign objects in the waveguide will cause performance degradation and may damage or destroy the unit.
- Any foreign objects in the antenna will cause performance degradation and possible device damage.
- For 1 mm connectors proper torque should be applied: 4.0 ± 0.15 inch-pounds (0.45 ± 0.02 Nm).
  Torque wrench model <u>SCH-06004-S1</u> is highly recommended.
  - For 1.35 mm, 1.85 mm, 2.4 mm, 2.92 mm, and SMA connectors proper torque should be applied: 8.0 ± 0.15 inch-pounds (0.90 ± 0.02 Nm). Torque wrench model <u>SCH-08008-S1</u> is highly recommended.

### SAG-6838634501-12-S1

#### Typical Antenna Pattern @ 68 GHz



Typical Antenna Pattern @ 77 GHz



www.eravant.com | 424-757-0168 | support@eravant.com Copyright © 2022 by Eravant

### SAG-6838634501-12-S1

#### Typical Antenna Pattern @ 86 GHz





#### **Typical Gain vs. Frequency**

www.eravant.com | 424-757-0168 | support@eravant.com Copyright © 2022 by Eravant

## ERAVANT

### SAG-6838634501-12-S1

Typical Return Loss Vs Frequency



# ERAFANT NEXT GENERATION MILLIMETERWAVE COMPONENTS