## SWX-17426410-04-4B

www.eravant.com | 424-757-0168 | support@eravant.com

Copyright © 2023 by Eravant

## Waveguide Crossguide Coupler, WR-04 Band, 10 dB

**SWX-17426410-04-4B** is a four-port, split block crossguide coupler that is offered for power sampling where directivity is of no concern. Compared to a multi-hole directional coupler, crossguide couplers offer lower insertion loss and a smaller form factor and insertion length. This model operates between 170 to 260 GHz with a 10 dB typical coupling level and 2.5 dB nominal insertion. The input, output, and coupled ports are all WR-04 waveguides with UG-387/U-M anti-cocking flanges.

### **Electrical Specifications:**

Parameter	Minimum	Typical	Maximum
Frequency	170 GHz		260 GHz
Insertion Loss*		2.5 dB	
Coupling		10 dB	
Directivity		10 dB	
Return Loss		18 dB	
Specification Temperature		+25°C	
Operating Temperature	-40°C		+85°C

\*Performance may be reduced at band edges.

#### **Mechanical Specifications:**

Item	Specification
Waveguide Ports	WR-04 Waveguide with UG-387/U-M Anti-Cocking Flange
Material	Aluminum
Finish	Gold Plated
Weight	0.9 Oz
Outline	WX-B04-4-F4-A

# ERAWANT



EAR99	

ECCN

## FEATURES

- Full Band Operation
- Low Insertion Loss
- Moderate Directivity
- Four Port Configuration

#### **APPLICATIONS**

- Test Labs
- Instrumentations
- Sub-assemblies

#### SUPPLEMENTAL DETAILS



# SWX-17426410-04-4B

# ERA\ANT

### **Mechanical Outline:**

Unless otherwise specified, all dimensions are in inches [millimeters])



#### NOTE:

- On condition that test data is provided it is collected from a sample lot. Actual data may vary slightly from unit to unit. All testing is performed under +25 °C room temperature.
- On condition that simulated test data is provided, actual measured data may slightly vary.
- Eravant reserves the right to change the information presented without notice.

#### CAUTION:

• If a waveguide is present, any foreign objects in the waveguide will cause performance degradation and may damage or destroy the unit.

# MAKING MILLIMETERWAVE ACCESSIBLE