

Ka-Band Varactor Tuned Gunn Oscillator, 34 GHz, ± 250 MHz Bandwidth

Description:

Model SOV-34305216-28-G1 is a Ka-Band, Varactor tuned Gunn oscillator that utilizes a high performance GaAs Gunn diode and proprietary cavity design to deliver +16 dBm typical power. The oscillator features a Varactor tuning range of ± 250 MHz and delivers low AM/FM noise and harmonic emissions. Compared to its counterparts, such as multiplier based sources, the Gunn oscillator is a lower cost and cleaner source. The center frequency of the oscillator can be mechanically trimmed within ± 250 MHz using the self-locking set screw. The performance of the oscillator can be further enhanced by adding an isolator, Gunn oscillator modulator/regulator and temperature heater.



Features:

- Low AM/FM Noise and Harmonics
- Mechanical Frequency Trimming

Applications:

- Test Sources
- Signal Generation
- FMCW Radar Systems
- Communication Systems

Electrical Specifications:

Parameter	Minimum	Typical	Maximum
Center Frequency		34.0 GHz	
Power Output		+16 dBm	
Mechanical Tuning Range		± 250 MHz	
Varactor Tuning Range		± 250 MHz	
Bias Voltage		+5.0 V _{DC}	+5.5 V _{DC}
Bias Current		800 mA	
Varactor Tuning Voltage Range	0 V _{DC}		+25 V _{DC}
Specification Temperature		+25°C	
Operating Temperature	0°C		+50°C


Mechanical Specifications:

Item	Specification
RF Port	WR-28 Waveguide with UG-599/U Flange, 4-40 Threaded Holes
Bias Port	Solder Pins
Tuning Port	SMA (F)
Mechanical Trimming Mechanism	Self-Locking Set Screw
Housing Material	Aluminum
Finish	Gold Plated
Weight	4.0 Oz
Outline	OV-SA-C-2



Ka-Band Varactor Tuned Gunn Oscillator, 34 GHz, ± 250 MHz Bandwidth

Mechanical Outline: (Unless otherwise specified, all dimensions are in inches [millimeters])



Note:

- All data presented is collected by using a sample lot for illustration purpose. Actual data is different unit to unit.
- The data given above was tested under case temperature **+35 °C**.
- The SAGE Millimeter Gunn oscillator regulator **SOR-R3** is highly recommended for over voltage and reverse bias protection. The outline of the model SOR-R3 is shown in below.
- SAGE Millimeter, Inc. reserves the right to change the information presented without notice.

Caution:

- Reversing polarity will destroy the device.
- Gunn diode bias voltage should never exceed **+5.5 Volts** and Varactor bias voltage should never exceed **+25 Volts**.
- The case temperature of the device should never exceed **+50°C**. Use an additional heatsink or fan if necessary.
- Proper torque, 8.0 ± 0.15 inch-pounds (0.90 ± 0.02 Nm), should be applied. **SAGE Millimeter torque wrench, model SCH-08008-S1, is highly recommended.**
- Any foreign objects in the waveguide will destroy the device.



Ka-Band Varactor Tuned Gunn Oscillator, 34 GHz, ±250 MHz Bandwidth

Appendix: The Outline of the Gunn Oscillator Regulator Model SOR-R3

