# STF-28-S1-WP

## **Ka-Band Faraday Isolator**

### **Description:**

**Model STF-28-S1-WP** is a full band Faraday isolator that operates from 26.5 to 40 GHz. The Faraday isolator is constructed with a longitudinal, magnetized ferrite rod that causes a Faraday rotation of the incoming RF signal. The Faraday isolator offers 30 dB typical isolation and a 1.2 dB nominal insertion loss with good flatness. The return loss of the isolator is 14 dB. The input and output ports have WR-28 waveguides with UG-599/U flanges.

#### **Features:**

- Full Waveguide Band Operation
- Moderate Insertion Loss
- High Isolation
- Instrumentation Grade

### **Electrical Specifications:**

**Applications:** 

**Test Labs** 

Instrumentations

Sub-assemblies

Parameter	Minimum	Typical	Maximum
RF Frequency*	26.5 GHz		40 GHz
Insertion Loss		1.2 dB	2.0 dB
Isolation		30 dB	
Return Loss		14 dB	1 33
Power Handling		1.8 W (CW)	2.0 W (CW)
Specification Temperature		+25 °C	
Operating Temperature	-40 °C		+85 °C

\*Note: The operating bandwidth can be extended to 24 to 42 GHz.

## Mechanical Specifications:

Item	Specification
RF Input and Output	WR-28 Waveguide with UG-599/U Flange
Waveguide Flange Material	Brass
Waveguide Flange Finish	Gold Plated
Cover Material	Aluminum
Cover Finish	Black Anodized
Weight	4.6 Oz
Insertion Length	2.69"
Outline	TF-SA



www.sagemillimeter.com | 3043 Kashiwa Street, Torrance, CA 90505 Phone: 424-757-0168 | Fax: 424-757-0188 | Email: sales@sagemillimeter.com lillimeter, In

Rev 1.0

# STF-28-S1-WP

# **Ka-Band Faraday Isolator**

## **Typical Performance vs. Frequency**



## **Typical Return Loss vs. Frequency**



Phone: 424-757-0168 | Fax: 424-757-0188 | Email: sales@sagemillimeter.com

SAGE Millimeter, Inc.

# **STF-28-S1-WP**

# **Ka-Band Faraday Isolator**

**Mechanical Outline:** (Unless otherwise specified, all dimensions are in inches [millimeters])



#### Note:

- All data presented is collected from a sample lot. Actual data may vary unit to unit.
- All testing was performed under +25°C case temperature.
- The model with orthogonal input and output ports is offered under model number **STF-28-91**.
- The compact version is offered under model number STF-28-S1-C.
- Other custom mechanical configurations are available under different model numbers.
- Other mechanical configurations are available under different model numbers.

#### **Caution:**

- Exceeding absolute maximum ratings will damage the device.
- The device is sensitive to magnetic fields. Always keep magnet fields 6 inches away.
- Any foreign objects in the waveguide will cause performance degradation and possible device damage.



www.sagemillimeter.com | 3043 Kashiwa Street, Torrance, CA 90505 Phone: 424-757-0168 | Fax: 424-757-0188 | Email: sales@sagemillimeter.com