

W-Band Micrometer Driven Phase Shifter

Description:

Model STP-18-10-M2-WPC is a W Band micrometer driven phase shifter that covers the frequency range of 75 to 110 GHz. The phase shifter has a micrometer dial which allows for repeatable phase shift settings. The phase shifter is an ideal piece of equipment in waveguide systems where broadband phase shifting is required. The phase shifter exhibits a 0.5 dB typical insertion loss and an adjustable phase range of up to 180 degrees.



Features:

- Full Band Coverage
- Low Cost
- Convenient Mechanical Setting

Applications:

- Test Lab
- Instrumentations
- Manual Test Set

Electrical Specifications:

Parameter	Minimum	Typical	Maximum
RF Frequency Range	75 GHz		110 GHz
Insertion Loss		0.5 dB	
Phase Shifting Range	0 to 180°		
VSWR		1.3:1	
Power Handling		600 mW	800 mW
Specification Temperature		+25°C	
Operating Temperature	-40°C		+85°C

Mechanical Specifications:

Item	Specification
RF Input	WR-10 Waveguide with UG-387/U-M Flange
RF Output	WR-10 Waveguide with UG-387/U-M Flange
Setting	Micrometer Head
Insertion Length	3.0"
Flange Material	Brass
Finish	Gold Plated Waveguide Faces; Black Painted Body
Weight	4.0 Oz
Outline	TP-MW-BX1



