## STP-18-34-M1

### WR-34 Micrometer Driven Phase Shifter, Head Locking Screw, 22 to 33 GHz

### **Description:**

**Model STP-18-34-M1** is a WR-34 micrometer driven phase shifter that covers the frequency range of 22 to 33 GHz. The phase shifter features a precision micrometer dial with a knurled head locking screw, which allows for stable, repeatable settings that can be locked at any phase shift value. The phase shifter is an ideal piece of equipment in waveguide systems where broadband phase shifting is required. The phase shifter exhibits a 0.3 dB typical insertion loss and an adjustable phase range of up to 180 degrees.



### **Features:**

- Full Band Coverage
- Head Locking Screw
- Precision Machined Housing
- Convenient Mechanical Setting

### **Electrical Specifications:**

# Applications:

- Test Lab
- Instrumentations
- Manual Test Set

Parameter	Minimum	Typical	Maximum
Frequency Range	22 GHz		33 GHz
Insertion Loss		0.3 dB	
Phase Shifting Range		0 to 180°	
Return Loss		20 dB	
Power Handling		1 W (CW)	1.2 W (CW)
Specification Temperature		+25 °C	
Operating Temperature	-40 °C		+85 °C

### **Mechanical Specifications:**

ltem	Specification	
RF Ports	WR-34 Waveguide with UG-1530/U Flange	
Setting Type	Head Locking Screw Type Micrometer	
Micrometer Pitch	0.5mm	
Micrometer Resolution	0.01mm	
Insertion Length	4.0"	
Material	Brass	
Finish	Gold Plated	
Weight	9.0 Oz	
Outline	TA-M3	



www.eravant.com | 501 Amapola Ave, Torrance, CA 90501 Phone: 424-757-0168 | Fax: 424-757-0188 | Email: sales@eravant.com

### WR-34 Micrometer Driven Phase Shifter, Head Locking Screw, 22 to 33 GHz



**Typical Measured Insertion Loss vs Frequency** 

Mechanical Outline: (Unless otherwise specified, all dimensions are in inches [millimeters])





www.eravant.com | 501 Amapola Ave, Torrance, CA 90501 Phone: 424-757-0168 | Fax: 424-757-0188 | Email: sales@eravant.com

### WR-34 Micrometer Driven Phase Shifter, Head Locking Screw, 22 to 33 GHz

Note:

- All data presented is collected from a sample lot. Actual data may vary unit to unit, slightly.
- All testing was performed under +25 °C case temperature.
- Eravant reserves the right to change the information presented without notice.

#### Caution:

- RF power should never exceed 1.2 W.
- Forcing the micrometer down after encountering resistance may damage the dielectric sheet inside. This will cause permanent performance degradation and decrease the long-term stability and repeatability of the device.
- Attempting to adjust the micrometer setting while the head locking screw is engaged may damage the micrometer and decrease the long-term stability and repeatability of the device.
- Any foreign objects in the waveguide will cause performance degradation and possible device damage.





www.eravant.com | 501 Amapola Ave, Torrance, CA 90501 Phone: 424-757-0168 | Fax: 424-757-0188 | Email: sales@eravant.com