



Q Band, Compact Bandpass Filter, 45 GHz Center Frequency, 2nd Harmonic Rejection

Description:

Model SWF-45301110-22-B1-C is a Q band iris resonance based compact bandpass filter with a passband center frequency of 45 GHz and rejection frequency at 90 GHz. It is designed for any oscillator with an output waveguide of WR-22 with a UG-599/U flange pattern to pass the fundamental frequency at 45 GHz and reject the second harmonic at 90 GHz. The nominal insertion loss of the filter at 45 GHz is 0.5 dB and the rejection at 90 GHz is 13 dB. This filter can be used with SAGE Millimeter's Q-band volume production oscillator with model number SOL-45316-22-G1 to suppress the second harmonic content at 90 GHz.



Features:

- Low Cost
- Low Insertion Loss
- Compact Size

Applications:

- Second Harmonic Rejection
- Waveguide Components
- Sub-assemblies

Electrical Specifications:

Parameter	Minimum	Typical	Maximum
Passband Frequency	43 GHz	45 GHz	46 GHz
Passband Insertion Loss		0.5 dB	
Passband Ripple		±0.5 dB	
Rejection Frequency		90 GHz	
Rejection (2 nd Harmonic)		13.0 dB	
Specification Temperature		+25 °C	
Operating Temperature	-40 °C		+85 °C

Mechanical Specifications:


Item	Specification
Waveguide Port	WR-22 Waveguide with UG-599/U Flange
Material	Aluminum
Finish	Gold Chem Film
Weight	0.3 Oz
Size	0.750" (L) X 0.750" (L) X 0.050" (T)
Outline	WF-BQ-C






Q Band, Compact Bandpass Filter, 45 GHz Center Frequency, 2nd Harmonic Rejection

Measured Insertion Loss vs. Frequency



Mechanical Outline: (Unless otherwise specified, all dimensions are in inches [millimeters])



Note:

- All data presented is collected from a sample lot. Actual data may vary unit to unit.
- All testing was performed under +25 °C room temperature.
- SAGE Millimeter, Inc. reserves the right to change the information presented without notice

Caution:

- Any foreign objects in the waveguide will cause performance degradation and possible device damage.

