# SWB-05090-E1

## WR-05 E-Plane Waveguide Bend, 90°, Precision Machined

#### **Description:**

**Model SWB-05090-E1** is a 90°, WR-05 E-plane waveguide bend with UG-387/U-M Anti-Cocking flanges. The bend radius is 0.75". The waveguide bend covers the frequency range of 140 to 220 GHz. The waveguide bend is manufactured with precision machining as a split-block body, which results in a robust, reinforced mechanical structure that will not flex or bend compared to traditional waveguide sections made with thin-wall tubing and brazed joints. Other bend angles and bend radius are available under different model numbers.



- Frequency Range: 140 to 220 GHz
- Sturdy Split-Block Mechanical Structure



### **Applications:**

- Test Instrumentation
- Sub-assemblies

#### **Electrical Specifications:**

Parameter	Minimum	Typical	Maximum
Frequency	140 GHz		220 GHz
Insertion Loss		2.3 dB	
Return Loss		23 dB	
Specification Temperature		+25 °C	
Operating Temperature	-40 °C		+85 °C

#### **Mechanical Specifications:**

Item	Specification
Waveguide Size	WR-05 Waveguide with UG-387/U-M Anti-Cocking Flange
Bend Plane	E Plane
Bend Angle	90 Degrees
Bend Radius Length (A)	0.75″
Bend Radius Length (B)	0.75″
Material	Brass
Finish	Gold Plated
Weight	1.2 oz.
Outline	WB-EG-A-SB-L



www.eravant.com | 501 Amapola Ave, Torrance, CA 90501 Phone: 424-757-0168 | Fax: 424-757-0188 | Email: support@eravant.com

## WR-05 E-Plane Waveguide Bend, 90°, Precision Machined

Mechanical Outline: (Unless otherwise specified, all dimensions are in inches [millimeters])



#### Note:

• Eravant reserves the right to change the information presented without notice.





www.eravant.com | 501 Amapola Ave, Torrance, CA 90501 Phone: 424-757-0168 | Fax: 424-757-0188 | Email: support@eravant.com